

Size: 6.00" x 4.00" x 2.63", Cat #: PB30, Mfr: Reliance Controls.

Page 1 POWER INLET BOX CAT. NO. PB30 30 Amps., 120/240 VAC INSTALLATION INSTRUCTIONS
IMPORTANT: Installation of this power inlet box and related wiring must be done by a qualified ...

Model: PB30 Model Description: Power Inlet Box Max. Generator Running Watts: 7500 Max. Generator Input: 30A@125/250VAC Dimensions H x W x D (inches): 6 x 4 x 2.63 Cabinet Type, NEMA: ...

The power inlet box has rear knockout holes for mounting on the wall and offers large space for wiring, but no parts to mount it.

Model: PB30 Model Description: Power Inlet Box Max. Generator Running Watts: ...

The Reliance PB30 Power Inlet Box is an outdoor-rated electrical inlet box that serves as the permanent connection point between your portable generator and your home's transfer switch or ...

Reliance PB30 Power Inlet Box, 30A, 120/240V, L14-30P Technical Description: Raintight Type; Powder Coated Steel Material; L14-30P Configuration; UL (Canada and Us) Approval; 125/250 VAC Voltage ...

Scalable Capabilities; Innovative Design

Page 10 Transfer Equipment Specifications (S1104TE) Price List Page 6 ACCESSORIES Power Inlet Boxes PB 2.5 lbs PR 5 lbs Catalog Number Max.

Our 30 amp generator inlet box, designed for any transfer switch, generator-ready load center, and many stand-alone applications, offers a seamless and versatile solution.

Reliance Controls Reliance Controls PB30 Power Inlet Box, 125/250 VAC, 30 A, 3R NEMA Rating SKU: RTSPB30 Manufacturer Part Number: PB30 UPC: 78539930901 JUMP TO

Web: <https://tlaetsoglobal.co.za>